DC-AC Inverter

EuroCB series of DC-AC Inverter provides solution for the mobile supply of AC electrical power for your computer and/or home appliances when you are on the move. Standard features of the Inverter includes full electronic protection against short circuit, overload, over temperature and low voltage input with auto shutdown in low battery situation.

Model	I250FR12 / I250FR24
Input Voltage	11-15VDC / 20-30VDC
Output Voltage	110VAC or 220VAC
Output Power	250 watt (continous)
	500 watt (peak)
Output Frequency	50 / 60 Hz
Voltage stability	5%
Efficiency	Greater than 90%
Max. consumption	12V-30A / 24V-15A
Dimension	150 x 95 x 55 mm
Weight	Approx. 0.63 KG
	1

I400FR12 / I400FR24
11-15VDC / 20-30VDC
110VAC or 220VAC
400 watt (continous)
600 watt (peak)
Modified Sinewave
5%
Greater than 90%
12V-30A / 24V-15A
150 x 95 x 55 mm
Approx. 0.63 KG

I600FR12 /I600FR24
11-15VDC / 20-30VDC
110VAC or 220VAC
600 watt (continous)
1200 watt (peak)
Modified Sinewave
5%
Greater than 90%
12V-50A / 24V-25A
250 x 150 x 73 mm
Approx. 0.63 KG

Model	I1K2FR12 / I1K2FR24
Input Voltage	11-15VDC / 20-30VDC
Output Voltage	110VAC or 220VAC
Output Power	1200 watt (continous)
	2400 watt (peak)
Output Frequency	Modified Sinewave
Voltage stability	5%
Efficiency	Greater than 90%
Max. consumption	12V-100A / 24V-50A
Dimension	250 x 150 x 146 mm
Weight	Approx. 3.10 KG







